

CONNECTORS USED :


PART DESCRIPTION	PART NAME	MANUFACTURER	QTY
PIN HEADER (INPUT SIDE CN1)	B3P-5-VH	J.S.T	1
PIN HEADER (OUTPUT SIDE CN2)	B4P-VH	J.S.T	1

MATCHING HOUSINGS & PINS :
* NOT INCLUDED WITH THE PRODUCT.

PART DESCRIPTION	PART NAME	MANUFACTURER	QTY
SOCKET HOUSING (CN1)	VHR-5N	J.S.T	1
SOCKET HOUSING (CN2)	VHR-4N	J.S.T	1
TERMINAL PINS (CN1,2)	SVH-21T-P1.1	J.S.T	7

HAND CRIMPING TOOL : YC-160R CN1,2 MANUFACTURER : J.S.T

NAME PLATE



NOTES

- A : THE 4XØ3.5 HOLES ARE CUSTOMER CHASSIS MOUNTING HOLES. ALL MUST BE SCREWED IN ORDER TO CONFORM THE VIBRATION SPEC.
- B : MODEL NAME, NOMINAL OUTPUT VOLTAGE, MAXIMUM OUTPUT CURRENT ARE SHOWN HERE IN ACCORDANCE WITH THE SPECIFICATIONS.
- C : COUNTRY OF MANUFACTURE WILL BE SHOWN HERE.
- D : TO KEEP THE DISTANCE MORE THAN 2mm BETWEEN PC-BOARD EDGE AND CUSTOMER CHASSIS.
- E : C-UL-US , TUV AND CE MARKS FOR 3.3V, 5V, 12V, 15V, 24V, 36V, 48V ONLY.

(unit : mm)

MODEL NAME	VS30C
DENSEI-LAMBDA	